

VIS-1 KVM Extender



1000m KVM Station
 1600 x 1200 @ 60 Hz (DVI, RGB), 1280 x 1024 @ 100Hz (Stereo)
 RGB DVI
 PS/2, SUN, USB
 2 Fiber

- 1000m Fiber Optic KVM 가
- Thinklogical KVM Extender
- 2 Multi-mode Fiber 가 ()
- USB Tablet, USB , Human Interface Devices(HID)
- PS/2, SUN Legacy, USB /
- CPU (KVM Transmitter)
- Duplex Stereo Audio
- 165MHz VESA Standard RGB DVI
- 3D Stereo Graphics Emitter
- BNC
- DVI RGB DVI RGB 가
- (DB9) Tablet

• RGB , Receiver 3가
 Sync Configuration, RGBHV(Separate H & V),
 RGSB(Sync on green) RGBH/V(Composite)
 Legacy 110-240VAC
 가

Application



<VIS-1 KVM Extender Connection Diagram>

Specification

	DVI : 1600 x 1200 @60Hz RGB : 1600 x 1200 @60Hz Stereo : 1280 x 1024 @ 100Hz
	1000m
	100-240VAC, 47-63Hz Universal AC Power Supply
	10watts
	0 ~ 50
	5 ~ 95% RH, Non-condensing
	43.82 x 35.56 x 8.9 cm (W x D x H)
	4.4kg
Rack	EIA 19"
Optical Cable	Dual Fiber Multi-Mode 50 Micron () 62.5

VIS-1 Fiber Optic KVM Extender Source가
 Transmitter , Receiver
 , 2 Multimode Fiber Transmitter
 Receiver .

VIS-1 Fiber Optic KVM Extender RGB DVI
 USB, PS/2, SUN(Legacy) ,
 , USB Tablet, Full Duplex Stereo Audio, Serial 3D
 Application Stereo Graphics Emitter .

VIS-1 Digital Fiber Optic Transmitter/Receiver .
 Audio, Stereo Graphics Emitter , USB, Serial,
 Transmitter

Fiber VIS-1 Fiber Optic KVM Receiver .
 Transmitter Receiver 2 Fiber 1 Fiber
 1 KVM

Receiver Transmitter RGB
 DVI
 DVI

VIS-1 KVM Extender

Copper	
RGB Video to Computer	HD15 to DVI-I Male to Male, 1.8m (1)
DVI Video to Computer	DVI-I to DVI-I Male to Male, 1.8m (1)
USB Keyboard / Mouse to Computer	USB A to B, 1.8m (2)
PS/2 Keyboard / Mouse to Computer	MiniDIN 6, Male to Male, 1.8m (2)
SUN Keyboard / Mouse to Computer	MiniDIN 8, Male to Male, 1.8m (1)
Audio to Computer	3.5mm, Male to Male, 1.8m (2)
Serial to Computer	DB9, Male to Female, 1.8m (1)
Stereo Emitter to Computer	BNC, Male to Male, 50 Ohm, 1.8 m (1)

Copper Connector	
Video (Transmitter)	DVI-I (2)
Video (Receiver)	DVI-I (1)
Audio MIC	3.5mm Jack (Transmitter Receiver)
Audio MIC	3.5mm Jack (Transmitter Receiver)
Audio Line	3.5mm Jack (Transmitter Receiver)
Serial Port (Transmitter)	DB9 Female
Serial Port (Receiver)	DB9 Male
Stereo Emitter Input (Transmitter)	BNC
Stereo Emitter Input (Receiver)	BNC
USB Keyboard/Mouse	USB A (Transmitter Receiver)
USB Local Keyboard /Mouse	USB A (Transmitter)
PS/2 Keyboard/Mouse	MiniDIN 6 Female (Transmitter Receiver)
PS/2 Local Keyboard/Mouse	MiniDIN 6 Female (Transmitter)
SUN Keyboard/Mouse	MiniDIN 8 Female (Transmitter Receiver)
SUN Local Keyboard/Mouse	MiniDIN 8 Female (Transmitter)
USB Keyboard / Mouse from CPU	USB B (Transmitter)
Download USB	USB B (Transmitter Receiver)
Fiber Connector	ST, SC LC

Ordering Information

VIS-000001-ST	KVM X-tender System Pair, ST
VIS-000001-SC	KVM X-tender System Pair, SC
VIS-000001-LC	KVM X-tender System Pair, LC
VIS-000001-STTX	KVM X-tender System Transmitter, ST
VIS-000001-SCTX	KVM X-tender System Transmitter, SC
VIS-000001-LCTX	KVM X-tender System Transmitter, LC
VIS-000001-STRX	KVM X-tender System Receiver, ST
VIS-000001-SCRX	KVM X-tender System Receiver, SC
VIS-000001-LCRX	KVM X-tender System Receiver, LC



<VIS-1 KVM Extender Transmitter >



<VIS-1 KVM Extender Receiver >