

Fiber Converter- Rack Mount

[FRM301 Series]



FRM 301 Series 3U Media Converter Rack 16
 Converter Redundant Power SNMP
 Management 가 10Base-T, 100Base-TX,
 10 / 100 Base Multi Mode(2km) Single Mode
 (120km) Fiber, WDM(20km) Converter Card

FRM301 Series – Line Card Type

- IEEE 802.3u 100Base-FX 100Base-TX
- WDM Converter Fiber Cable TX RX
- Single Mode 120km
- ST, SC 9/125μm Single Mode Fiber
- RJ-45 Straight Cross-Over
- Full-Duplex, Half-Duplex, Auto
- 6 LED

LED		
PWR	Light	Power On
	Flash	SNMP
U / 100	Light	100M
	Off	10M
F / Full	Light	FX Port Full Duplex
	Off	FX Port Half Duplex
U / Full	Light	UTP Port Full Duplex
	Off	UTP Port Half Duplex
F / Link	Light	FX Port Link
	Off	FX Port Link

- 2 DIP Switch Setting
 - SW1 : FX Port Duplex Setting
 - SW2 : Loop Back Test Function Setting
- * SW2가 On LED Remote CPE Unit
- Link-Loss-Forwarding
 - DIP Switch Loop-Back
 - DIP Switch Remote
- 가 Frame Length
 - 1518 / 1522 Bytes for Normal
 - 1536 / 1536 Bytes for Special

FRM301 Series – Rack Mount Type

- 3U , 16 (16)
- Redundant Power Dual Power Module, Cooling Fan
- 가 (AC110~240V, DC24V, DC48V)
- , Cooling Fan
- SNMP Window Base GUI 가

[FRM401 Series]



FRM 401 Series 4 Converter
 Converter Card 12 (48
). Single Mode Multi Mode ST,
 SC, MT-RJ , Single Mode
 120km . Converter Card
 Fiber Cable Chassis
 RJ-45 Ethernet

Rack Mount Type FRM401 Series

- 4U , 19" 가
- Converter Card 12 Slot
- Converter Card 4 Fiber Converter
- 48 Converter(12 * 4 Converter)
- 10Mbps Card IEEE 802.3, 10 Base-T 10-Base-FL
- 100Mbps Card 802.3u, 100Base-TX 100Base-FX
- 10 / 100Mbps Card 802.3 10Base-T, 802.3u 100Base-TX 100Base-FX
- 10 / 100 WDM Card TX RX Fiber
- SNMP Card Slot
- Redundant Power Supply
- Cooling Fan Alarm
- Half Duplex, Full Duplex, Auto Negotiation
- 110VAC, 220vac, +24VDC, -48VDC
- Link Loss Forwarding
 - DIP Switch Loop Back Test
 - DIP Switch Remote
- 가 Frame Length
 - 1518 / 1522 Bytes for Normal
 - 1536 / 1536 Bytes for Special

